


**Fixture Lengths**

**CSS-R | RAS**

Fixture Type

Approval

**Continuous Run Individual Cable Centers**



**Stand Alone Cable Centers & Overall Length**



Fixture Length	Cable/Arm Centers (in)	Fixture Length	Cable/Arm Centers (in)	Fixture Length	Cable/Arm Centers (in)
2'	24.375"	2'	24.375"	2'	24.375"
3'	36.250"	3'	36.250"	3'	36.250"
4'	48.000"	4'	48.000"	4'	48.000"
6'	70.500"	6'	70.500"	6'	70.500"
7'	82.313"	7'	82.313"	7'	82.313"
8'	94.125"	8'	94.125"	8'	94.125"

Fixture Length	Cable/Arm Centers (in)	Overall Length (in)
2'	24.375"	25.500"
3'	36.250"	37.375"
4'	48.000"	49.125"
6'	70.500"	71.625"
7'	82.313"	83.438"
8'	94.125"	95.250"

**Continuous Run Lengths and Fixture Length Segments**


Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
9	8' - 9.125"	6-3
10	9' - 8.875"	6-4
11	10' - 8.688"	7-4
12	11' - 8.500"	8-4
13	12' - 7.188"	7-6
14	13' - 7.000"	8-6
15	14' - 6.813"	8-7
16	15' - 6.625"	8-8
17	17' - 5.625"	8-6-4
18	18' - 5.438"	8-7-4
19	19' - 5.250"	8-8-4
20	20' - 3.938"	8-7-6
21	21' - 3.750"	8-8-6
22	22' - 3.563"	8-8-7

Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
23	23' - 3.375"	8-8-8
24	24' - 2.625"	8-8-6-3
25	25' - 2.375"	8-8-6-4
26	26' - 2.188"	8-8-7-4
27	27' - 2.000"	8-8-8-4
28	28' - 0.688"	8-8-7-6
29	29' - 0.500"	8-8-8-6
30	30' - 0.313"	8-8-8-7
31	31' - 0.125"	8-8-8-8
32	31' - 11.375"	8-8-8-6-3
33	32' - 11.125"	8-8-8-6-4
34	33' - 10.938"	8-8-8-7-4
35	34' - 10.750"	8-8-8-8-4
36	35' - 9.438"	8-8-8-7-6

Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
37	36' - 9.250"	8-8-8-8-6
38	37' - 9.063"	8-8-8-8-7
39	38' - 8.875"	8-8-8-8-8
40	39' - 8.125"	8-8-8-8-6-3
41	40' - 7.875"	8-8-8-8-6-4
42	41' - 7.688"	8-8-8-8-7-4
43	42' - 7.500"	8-8-8-8-8-4
44	44' - 6.000"	8-8-8-8-8-6
45	45' - 5.813"	8-8-8-8-8-7
46	46' - 5.625"	8-8-8-8-8-8
47	47' - 4.875"	8-8-8-8-8-6-3
48	48' - 4.625"	8-8-8-8-8-6-4
49	49' - 4.438"	8-8-8-8-8-7-4
50	50' - 4.250"	8-8-8-8-8-8-4

**Number of Lamps**

- 2' = (1) 2' lamp
- 3' = (1) 3' lamp
- 4' = (1) 4' lamp
- 6' = (2) 3' lamps
- 7' = (1) 4' lamp & (1) 3' lamp
- 8' = (2) 4' lamps



#825-00095  
V-0314