


Fixture Lengths

CSS-R | RAS

Fixture Type

Approval

Continuous Run Individual Cable/Arm Centers



Stand Alone Cable/Arm Centers & Overall Length



Fixture Length	Cable/Arm Centers (in)	Fixture Length	Cable/Arm Centers (in)	Fixture Length	Cable/Arm Centers (in)
2'	26.000"	2'	26.000"	2'	26.000"
3'	38.000"	3'	38.000"	3'	38.000"
4'	50.000"	4'	50.000"	4'	50.000"
6'	78.500"	6'	78.500"	6'	78.500"
7'	90.500"	7'	90.500"	7'	90.500"
8'	102.500"	8'	102.500"	8'	102.500"

Fixture Length	Cable/Arm Centers (in)	Overall Length (in)
2'	26.000"	27.125"
3'	38.000"	39.125"
4'	50.000"	51.125"
6'	78.500"	79.625"
7'	90.500"	91.625"
8'	102.500"	103.625"

Continuous Run Lengths and Fixture Length Segments


Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
9	8' - 7.625"	8
10	9' - 9.625"	6-3
11	10' - 9.625"	6-4
12	11' - 9.625"	7-4
13	13' - 2.125"	6-6
14	14' - 2.125"	7-6
15	15' - 2.125"	8-6
16	16' - 2.125"	8-7
17	17' - 2.125"	8-8
18	18' - 4.125"	8-6-3
19	19' - 4.125"	8-6-4
20	20' - 4.125"	8-7-4
21	21' - 4.125"	8-8-4
22	21' - 8.625"	7-7-6

Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
23	22' - 8.625"	7-7-7
24	23' - 8.625"	8-7-7
25	24' - 8.625"	8-8-7
26	25' - 8.625"	8-8-8
27	26' - 10.625"	8-8-6-3
28	27' - 10.625"	8-8-6-4
29	28' - 10.625"	8-8-7-4
30	29' - 10.625"	8-8-8-4
31	31' - 3.125"	8-8-7-6
32	32' - 3.125"	8-8-8-6
33	33' - 3.125"	8-8-8-7
34	34' - 3.125"	8-8-8-8
35	35' - 5.125"	8-8-8-6-3
36	36' - 5.125"	8-8-8-8-6-4

Nominal Length (ft)	CSS-R/RAS Overall Length (in)	Fixture Length Segments
37	37' - 5.125"	8-8-8-7-4
38	38' - 5.125"	8-8-8-8-4
39	38' - 9.625"	8-8-8-6-6
40	39' - 9.625"	8-8-8-7-6
41	40' - 9.625"	8-8-8-7-7
42	41' - 9.625"	8-8-8-8-7
43	42' - 9.625"	8-8-8-8-8
44	43' - 11.625"	8-8-8-8-6-3
45	44' - 11.625"	8-8-8-8-6-4
46	45' - 11.625"	8-8-8-8-7-4
47	46' - 11.625"	8-8-8-8-8-4
48	48' - 4.125"	8-8-8-8-7-6
49	49' - 4.125"	8-8-8-8-7-7
50	50' - 4.125"	8-8-8-8-8-7

Number of Lamps

2' = (2) 2' lamp	6' = (4) 3' lamps
3' = (2) 3' lamp	7' = (2) 4' lamp & (2) 3' lamp
4' = (2) 4' lamp	8' = (4) 4' lamps



#825-00076
V-0314